

## Quick installation guide for LB9007C-ST-R2

This installation guide gives step-by-step instructions on how to install LB9007C-ST-R2 module into LB9024A-R2 or LB9017A-R3

### Selecting a proper plug-in module

Fiber Plug-In Modules are available on Multi-mode with ST, SC, MT-RJ or VF-45 connectors and Single-mode with SC connectors. LB9007C-ST-R2 is a multi-mode FX with ST connector and LB9017C-SC-R2 is a multi-mode FX with SC connector. For MTRJ or VF-45 connector please contact Black Box Tech Support for special ordering information.

### Follow These Steps for Installation:

**Step 1:** Make sure the power is switched off. The module is not hot-swappable.



It may cause electric shock or any possible damage to the switch if the power is not switched off. Turn off the power before installation.

**Step 2:** Unscrew the cover plates of the expansion slot. Retain both the screws and the cover plates. The plates can be reinstalled if the module is removed.

**Step 3:** Remove the module from the static-free container then slowly slide the plug-in module into the designated slot, following the plastic guides.

**Step 4:** Snap in the Plug-In Module to attain a firm connection then fasten the screws retained from original cover plate.

**Step 5:** Restore power.





Figure 2: Removal of module cover plate

One port fiber module being installed

### CUSTOMER SUPPORT INFORMATION

Order toll-free in the U.S. 24 hours, 7 A.M. Monday to midnight Friday: 877-877-BBOX  
FREE technical support, 24 hours a day, 7 days a week: Call 724-746-5500 or fax 724-746-0746  
Mail order: **Black Box Corporation**, 1000 Park Drive, Lawrence, PA 15055-1018  
Web Site: [www.blackbox.com](http://www.blackbox.com) • E-mail: [info@blackbox.com](mailto:info@blackbox.com)